Ceiling LED Chandelier



START FROM HERE

- Make sure **POWER** is **COMPLETELY OFF** at the fuse box
- Have your fixture installed by a qualified licensed electrician
- · Prepare everything in a clear area
- · Wear gloves at all times during this installation
- · Read instructions carefully before you start assembly
- Keep this installation sheet for future reference

Please Note

- This Kuzco LED fixture comes with pre-wired LED module(s)
- Unless instructed, Do Not touch any part of the LED module(s) as any unnecessary contact with the module could cause permanent damage
- Use ELV (Electronic Low Voltage) or TRIAC type of dimmer for dimming application
- 120V input

Technical Support: 1-855-855-8926

- **1.** Remove fixture from its original package.
- 2. Separate mounting plate (1c) from canopy (2a) by removing canopy screws (2f).
- **3.** Attach mounting plate **(1c)** to electrical junction box **(1a)** using screws provided **(1e)** in hardware package.
- **4.** Secure mounting plate (1c) to mounting surface with anchors (1f) and screws (1g)
- between canopy (2a) and mounting plate (1c). Secure aircraft cable (2e) in aircraft barrel (2h) with screw and attach to a suitable supporting member in the ceiling (See Illustration 2). Determine hanging height of fixture by securing rods (2d) to canopy (2a) and fixture body (3b) after feeding fixture wires (LED+ and LED-) through rods.
- **6.** Make proper electrical connections between LED and DC driver, LED- Negative, LED+ Positive using quick connector provided (2g) (See Illustration 1 and refer to diagram on driver)
- **1.** Make proper electrical connections (Black to Hot "L", White to Neutral "N", Green to ground with orange wire nuts **(1b)** provided in hardware package
- **8.** Secure canopy (2a) to mounting plate (1c) with canopy screws (2f)
- **9.** Align, insert mounting hardware on back of shade (3a) onto fixture mounting plate (3c), rotate clockwise slightly to secure shade

