

Remote Transformer-150W EI 12v LED



DESCRIPTION

This remote electronic transformer converts standard 120 volt line-voltage to 12 volts, providing the necessary voltage for powering a MonoRail, Kable Lite, Wall MonoRail or FreeJack low-voltage lighting system. This remote electronic transformer can be used to power lamps totaling up to 150 watts. This transformer is equipped with fast-acting short circuit and overload protection that will safely turn off the system should a short occur. Once the short is removed, the unit can be reset by simply flipping the wall switch off and back on.



INSTALLATION

This transformer must be installed in a remote but accessible location (such as above the ceiling or in a closet). To simplify installation the transformer should be located no more than 20 feet from the run or power feed. The electrician will need to supply the proper gauge conductor from the transformer to the power feed location based on distance (see Low-Voltage Wire Size Table in the instruction sheet.)

OTHER

Input Wiring: Can be ordered to hard wire to a junction box or plug in with 16' power cord with plug. This transformer provides a single 150 watt output and must be used with a single feed canopy or other power feed option (sold separately). 12 volt output transformers require the use of 12 volt lamps.

WEIGHT

2.52lb / 1.14kg ±

ORDERING INFORMATION

700AT152EL

As a general rule when using LED fixtures we do not recommend using greater than 70% of specified maximum wattage on the transformer due to inrush current. for assistance, please contact our technical support department.



700AT152EL	
FIXTURE TYPE:	_____
JOB NAME:	_____
NOTES:	_____

