

access

LIGHTING

*****READ & SAVE THESE INSTRUCTIONS *****
ACCESS LIGHTING
MODEL 52070
INSTALLATION & OPERATION INSTRUCTIONS

1) TOOLS AND MATERIALS REQUIRED

- ❖ Blade Screwdriver
- ❖ Star Screwdriver
- ❖ Wire Cutters
- ❖ Wiring supplies as required by Electrical Code
- ❖ Step Ladder
- ❖ 1 x 60W/A-19(E-26 Medium Base) Bulb

Attention:

Before assembling your lighting fixture, please read the following instructions.

(2) GENERAL

1. To ensure the success of the installation, be sure to read these instructions thoroughly before beginning.
2. All electrical connections must be in accordance with local codes, ordinances, or the National Electrical Code. If you are unfamiliar with methods of installing electrical wiring, secure the services of a qualified licensed electrician.
3. These fixtures are intended for mounting to a standard 4" x 2 1/4" deep metal octagon outlet box. The box must be directly supported by the building structure and U.L. Recognized.
4. Before commencing with the installation, **disconnect the power by turning off the circuit breaker** or by removing the fuse at the fuse box. Turning the power off using the light switch is not sufficient to prevent electrical shock.

NOTE:

The important safeguards and instructions appearing in this manual are not meant to cover all possible conditions and situations that may occur. It must be understood that common sense, caution and care, are factors that cannot be built into any product. The person(s) caring for and operating the fixture must supply these factors.

(3) UNPACKING THE FIXTURE

On checking the contents of the box you will find;

1. Crossbar
2. Hardware Packet
3. Canopy
4. Metal Shade
5. Metal Housing
6. Strain Relief/Gripper
7. Finial
8. Thumb Nut

CAUTION:

- **Ensure that the Fitting is Cool and Switched off, Before Changing Bulbs.**
- **Do Not use Bulbs Exceeding Maximum Wattage , As Per Caution Label.**
- **Do Not Touch the Bulb while fixture is in operation.**
- **Do not place fixture in close proximity to combustible materials.**

(4) PREPARE THE FIXTURE

1. If you are replacing an existing fixture, disconnect and remove the old fixture. Expose the supply wiring from the outlet box.
2. Lay the un-assembled fixture on a soft surface and carefully remove all the packing material.
3. Slide the **Thumb Nut (10)** and **Canopy (9)** down the cord.
4. Determine the desired length of your fixture, cut the wires leaving an additional 1" to allow for connections.
5. Secure the **Threaded Pipe (8)** to the **Crossbar (1)**. Push the wire up through the **Threaded Pipe (8)** and **Crossbar (1)**.
6. Fit the wire through the **Gripper or Strain Relief (5)**, so that it is secure.
7. Attach the **Supply Wires** to the **Fixture Wires** in the following manner: The **Black supply wire** attaches to the **Black fixture wire** and the **White supply wire** attaches to the **White fixture wire**. Secure these connections with supplied **Wire Connectors** and tape these connections with U.L Listed electrical tape.
8. Attach the **Green/Ground wire** from the fixture to the **Electrical Supply Wire** or to the **Green Screw** located on the **Mounting Plate (crossbar)**. Tuck all of the wires into the **Junction Box**.
9. Secure the **Crossbar (1)** to the **Junction Box** with the supplied **Screws (1)**.
10. Move the **Canopy (9)** up the wire so that it is sitting flush to your mounting surface and secure it by moving the **Thumb Nut (10)** up the wire and screwing it into the bottom of the **Threaded Pipe (8)**.
11. Insert the a **60W/A-19 Medium Base Bulb** into the **Socket (14)** . **Do not exceed wattage as stated on warning label.**
12. Restore electricity and enjoy your new lighting fixture.

