



**⚠ WARNING/CAUTION**

- **DISCONNECT POWER BEFORE RE-LAMPING OR WIRING THE FIXTURE. READ ALL INSTRUCTIONS COMPLETELY BEFORE STARTING INSTALLATION.**
- **TO AVOID THE RISK OF FIRE OR SHOCK, FIXTURE MUST BE INSTALLED IN COMPLIANCE WITH ALL APPLICABLE NATIONAL AND LOCAL ELECTRICAL/BUILDING CODES. THE INSTALLATION AND MAINTENANCE OF THIS UNIT SHOULD BE COMPLETED BY A LICENSED ELECTRICIAN OR CERTIFIED FACTORY TRAINED TECHNICIAN.**
- **CALIFORNIA PROP 65: THIS LIGHTING FIXTURE CONTAINS CHEMICALS KNOWN TO THE STATE OF CALIFORNIA TO CAUSE CANCER, BIRTH DEFECTS, AND/OR OTHER REPRODUCTIVE HARM. WASH HANDS AFTER USE.**
- **REMOVE THE FIXTURE, PARTS AND PARTS BAG(S) FROM THE CARTON. BEFORE DISCARDING THE CARTON, DOUBLE CHECK TO MAKE CERTAIN THAT ALL PARTS ARE FOUND. INSPECT THE FIXTURE PRIOR TO INSTALLATION FOR ANY DAMAGE TO THE FIXTURE.**
- **DIMMING: THE FIXTURE CAN BE CONTROLLED BY A WALL DIMMING DEVICE. ONLY USE TRIAC/ELECTRONIC DIMMER. MAKE SURE THE CARTON IS MARKED FOR USE WITH LED COMPACT FLUORESCENT-INCANDESCENT LIGHT SOURCE ONLY. THESE CAN BE PROVIDED BY YOUR LOCAL ELECTRICAL DISTRIBUTOR, HOME CENTER, OR HARDWARE STORE.**
- **PLEASE CLEAN WITH A SOFT, DRY CLOTH ONLY! DO NOT USE CLEANSERS**

**FIXTURE INSTALLATION** (NOTE: USE LISTED LUMINAIRE JUNCTION BOX RATED FOR MINIMUM 90 LBS AND INSTALLED PER JUNCTION BOX INSTRUCTIONS)

1. Remove the outlet box from the approved support, and install additional support bracket (Not included)
2. Slide crimp type CABLE CLAMP (12) onto the SAFETY CABLE (11).  
Feed the SAFETY CABLE (11) down through one of the holes in the top of the outlet box.  
Loop the SAFETY CABLE (11) over the approved support.  
Feed the SAFETY CABLE (11) back through the top of the box and the CABLE CLAMP (12).  
  
Using the crimping tool, tightly crimp the CABLE CLAMP (12) to lock the SAFETY CABLE (11) in position.
3. Reinstall the outlet box to the approved support.
4. Attach the CROSSBAR (1) onto the junction box using the MOUNTING SCREWS (2). This fixture is designed to be mounted on a LISTED LUMINAIRE JUNCTION BOX RATED FOR MINIMUM 90 LBS. The junction box must be securely mounted to the structure of the building.
5. Open the end link on the CHAIN (3) and attach to the loop on the FIXTURE ASSEMBLY (4). Hang the FIXTURE ASSEMBLY (4) on the CHAIN (3) at your desired height, and remove excess CHAIN.
6. Feed the wire through the CHAIN (3), SCREW COLLAR (5), CANOPY (6), SCREW COLLAR LOOP (7), NIPPLE (8), and CROSSBAR (1), and screw the NIPPLE (8) onto the CROSSBAR (1).
7. Open the top link on the CHAIN (3), and Hang the FIXTURE ASSEMBLY (4) to the SCREW COLLAR LOOP (7).
8. Cut off excess wire, and strip the insulation off the end of the leads.
9. Attach the Ground wire (Green) to the ground inside the junction box (Generally green or bar copper wire) or the GROUND SCREW (9) on the MOUNTING PLATE (1). **NEVER CONNECT GROUND WIRE TO "HOT" WIRE! FAILURE TO FOLLOW THIS COULD RESULT IN SERIOUS INJURY OR DEATH!**
10. Connect the white fixture lead to the neutral (Generally white) wire in the outlet box. Fasten the wires together with an approved fastener (WIRE NUT) (10). Starting 1" below the fastener, tightly wrap the connection with electrical tape so that the connections seals the end of the fastener. **MAKE SURE THERE ARE NO EXPOSED WIRE OF STRANDS THAT COULD CAUSE A DANGEROUS SHORT CIRCUIT!**



ROUNDOUT  
1255  
INSTALLATION INSTRUCTIONS

ITEM	DESCRIPTION	PART NUMBER
1	CROSSBAR	X
2	MOUNTING SCREW	X
3	CHAIN	X
4	FIXTURE ASSEMBLY	X
5	SCREW COLLAR	X
6	CANOPY	X
7	SCREW COLLAR LOOP	X
8	1/4 NIPPLE	X
9	GROUND SCREW	X
10	WIRE NUT	X
11	SAFETY CABLE	X
12	CABLE CLAMP	X
13	BULB	X

FIXTURE INSTALLATION CONTINUED

11. Connect the black fixture leads to the hot (Generally black) wire in the junction box. Fasten the joined wires same as previous step. NEVER REVERSE HOT AND NEUTRAL WIRES. FAILURE TO FOLLOW THIS COULD RESULT IN SERIOUS INJURY OR DEATH!
12. Push the wires back into the junction box. Lift up the CANOPY (6) up to the ceiling, and screw the SCREW COLLAR LOOP (7) onto the SCREW COLLAR (5).
13. Screw the BULB (13) up into the SOCKET of the fixture. THIS FIXTURE IS RATED FOR 40 WATT TYPE G16.5 LAMP. DO NOT EXCEED THE RECOMMENDED WATTAGE!
14. Restore power to the outlet at the breaker or fuse box.