# W TRACK CURRENT LIMITER

# WAC LIGHTING

## 120V and 277V Track System


## Responsible Lighting®


#### **Low Cost Energy Code Compliance Made Easy**


- Easy to install and assures compliance to energy codes such as California Title 24 or ASHRAE 90.1 requirements in terms of power density
- If the track is overloaded the current limiter circuit breaker will trip and shut down power to the track.
- May be reset when the overall sum of fixture wattages are reduced below the circuit breaker rating

First on Ton	
Fixture Type:	
Catalog Number:	
Project:	

### Location:







120V W Track	Model		Rating	Circuit Breaker	Max Wattage	Finish		
	WEDL	Surface Mount						
Single Live end (Left)	WEDL-RT	Recessed Flanged	1/5A 1/2A 1A 2A 5A 7A 10A 12A	1/2A 2 X 0.5Amp 1A 2 X 1 Amp 2A 2 X 2.5Amp 5A 2 X 5 Amp 7A 2 X 7.5Amp 10A 2 X 10Amp	2 X 24W 2 X 60W 2 X 120W 2 X 300W 2 X 600W 2 X 900W 2 X 1200W 2 X 1440W	BK PT WT		
	WEDL-RTL	Recessed Flangeless					Black	
Single Live end (Right)	WEDR	Surface Mount					Platinum White	
	WEDR-RT	Recessed Flanged						
	WEDR-RTL	Recessed Flangeless						

Example: WEDL-1/5A-BK

277V W Track	Mod	del		Rating	Circuit Breaker	Max Wattage	Finish		
Single Live end (Left)	WH	IEDL	Surface Mount	1A 2A 5A 7A 10A 12A	2 X 1 Amp 2 X 2.5Amp 2 X 5 Amp 2 X 7.5Amp 2 X 10Amp 2 X 12Amp	2 X 277W 2 X 692W 2 X 1385W 2 X 2077W 2 X 2770W 2 X 3324W	BK PT WT	Black Platinum White	
	WH	IEDL-RT	Recessed Flanged						
	WH	IEDL-RTL	Recessed Flangeless						
Single Live end (Right)	WH	IEDR	Surface Mount						
	WH	IEDR-RT	Recessed Flanged						
	WH	IEDR-RTL	Recessed Flangeless						

Example: WHEDL-1A-BK

waclighting.com Phone (800) 526.2588 Fax (800) 526.2585 Headquarters/Eastern Distribution Center 44 Harbor Park Drive Port Washington, NY 11050 Central Distribution Center 1600 Distribution Ct Lithia Springs, GA 30122 Western Distribution Center 1750 Archibald Avenue Ontario, CA 91760