

Medallion Installation

What You May Need

Ladder, Adhesive Caulking, Caulking Gun, Screwdriver, Putty Knife

Preparation

1. **ALWAYS** turn off the electricity at the circuit breaker box.
2. Disconnect your current lighting fixture and remove it prior to installing your medallion. (See your lighting fixture instructions)
3. Apply desired non-laquer based paint finish to medallion before installing (optional).

Installation

1. Slip wires and chain through center hole of medallion, fixture canopy, and canopy screw.




Fig. 1

2. Re-connect fixture and wires. Carefully tuck wires back into wirebox.




Fig. 2

3. Lift medallion and fixture canopy to ceiling and secure firmly with canopy ring. (As an option before securing medallion to ceiling, a thin bead of latex adhesive or silicone caulk may be applied to back of medallion to eliminate possible gaps or sagging. Screws are also provided for this purpose in case additional strength is needed).




Fig. 3

Important Notes

1. Check with local electrical codes on the use of medallions before installing.
2. Your ceiling medallion functions as a decorative element only, and is not designed to support the weight of a lighting fixture.



www.elklighting.com



www.landmarklighting.com

12 Willow Lane, Nesquehoning, PA 18240
Ph: (800) 613-3261 Fax: (866) 613-3264
Email: sales@elklighting.com