

NUD-68 Series Bravo FROST LED 120V Linear Light Source: LED - 7 Watts / 500 Lumens per foot

PRODUCT DESCRIPTION

Nora Lighting's low-profile, Title 24 compliant fixtures provide excellent and even illumination on all surfaces. At only 7 watts per foot, Bravo FROST produces 500 lumens at a crisp sharp 95+ CRI. Each Bravo FROST contains its own driver allowing a 120V feed and longer single runs than low voltage systems. It is one of the most energy efficient products in the market. LED technology eliminates forward heat from the fixture, also no UV or infrared rays to harm artwork or heat sensitive foods.

FEATURES

- Architectural extruded aluminum construction
- Symmetrical internal reflectors produce broad even light
- Frosted Lens eliminates LED diode image
- 120V linear system
- 500 lumens / 7 Watts per foot
- 95+ CRI; R90 70+
- Available in 2700K, 3000K & 4000K CCT
- Available in 4 different lengths: 12", 18", 24", 32"
- Dimmable LEDs
- Linkable up to 400 Watts fixtures (about 50ft.)
- Less than 1" in depth.
- Self contained electronic driver in each unit
- 0° to 90° adjustable mounting brackets included
- Bronze and White finishes with Frosted Lens
- 50,000 hours of rated lamp life

Included with every Bravo FROST:

Two (2) angle adjustable mounting clip sets 0° - 90°.
 End to End Connector

Housing

Extruded Aluminum

Mounting

Angle adjustable mounting brackets (0° - 90°)

Dimming

Bravo Frost can only be dimmed with Electronic Low Voltage dimmer

ELECTRICAL

Voltage: 120V

Power Consumption: 7 Watts per foot

Lumens: 500 lm / ft

Color Rendering Index: >95 CRI

Light Source: LEDs

Life Expectancy: 50,000 Hours

Maximum Run Length: 400 Watts linked fixtures

Color Temperature: Warm White (2700K, 3000K), Cool White (4000K)

Labels and Warranty

cULus Listed for Dry Location
 Title 24 / JA8 - 2016 Compliant
 ENERGY STAR[®] Rated
 5 Year Warranty




Bravo FROST LED Linear Light (500 Lumens per foot)


CATALOG. NO.	LENGTH	WATTAGE / LUMEN	COLOR TEMP.	FINISH
NUD-68	12 = 12"	7W / 520L	/27 = 2700K	BZ = Bronze
	18 = 18"	10W / 757L	/30 = 3000K	W = White
	24 = 24"	13W / 978L	/40 ¹ = 4000K	
	32 = 32"	16W / 1212L		

¹ 4000K is only available in White Finish

DIMENSIONS



0-90° ADJUSTABILITY



ACCESSORIES

- NUA-602:** Junction Box
- NUA-603:** End to End Connector
- NUA-604:** 3-Wire Ground Hardwire Connector
- NUA-605:** 72" Cord and Plug
- NUA-606:** 6" Jumper Cable
- NUA-612:** 12" Jumper Cable
- NUA-624:** 24" Jumper Cable
- NUA-672:** 72" Jumper Cable
- NUA-609:** Adjustable Mounting Bracket

Create a complete item number: Example: NUD-6812/30W 12" 7W Bravo FROST, 3000K, White finish

BRAVO FROST 120V LED LINEAR LIGHT ACCESSORIES



Junction Box
NUA-602 BZ,W
 Used to power NUD-68 series using jumper cables or NUA-604. Includes On/Off switch



End to End Connector
NUA-603 BZ,W
 Used to join two NUD-68 series LED seamlessly together. One included with each Bravo FROST unit



3-Wire Ground Hardwire Connector
NUA-604 B,W
 Used to hardwire NUD-68 series LED fixture to NUA-602 or J-Box



72" Cord and Plug
NUA-605 B,W
 Convert NUD-68 series LED fixture from hardwire to direct plug-in unit




Jumper Cable (B,W)
NUA-606 6" **NUA-624** 24"
NUA-612 12" **NUA-672** 72"
 Connect two NUD-68 series LED fixture



Adjustable Mounting Bracket (set of 2)
NUA-609 BZ,W
 0-90 degree adjustable mount bracket. Two included with each Bravo FROST.


SAMPLE LAYOUT



Bravo LED 120V Linear Light Accessories

Junction box


Used to power NUD Series using Jumper Cables or NUA-404. Includes ON/OFF switch.



- NUA-602BZ:** Junction Box, Bronze
- NUA-602W:** Junction Box, White

End to End Connector


Use to join two NUD LED seamlessly together. One included with each unit.



- NUA-603B:** End to End Connector, Black
- NUA-603W:** End to End Connector, White

72" Hardwire Connector


3-Wire grounded connector/cable use to hardwire NUD Series LED fixture to NUA-402 or J-Box.



- NUA-604B:** 72" Hardwire Connector, Black
- NUA-604W:** 72" hardwire Connector, White

Jumper Cable


Used to join NUD Series LED fixtures together or to an NUA-602.



- NUA-606BZ:** 6" Jumper Cable, Black
- NUA-606W:** 6" Jumper Cable, White
- NUA-612BZ:** 12" Jumper Cable, Black
- NUA-612W:** 12" Jumper Cable, White
- NUA-624BZ:** 24" Jumper Cable, Black
- NUA-624W:** 24" Jumper Cable, White
- NUA-672BZ:** 72" Jumper Cable, Black
- NUA-672W:** 72" Jumper Cable, White

Adjustable Mounting Bracket


Brackets adjust from 0° to 90°. Two brackets are included with each Bravo and Bravo Plus unit.



- NUA-609BZ:** Adjustable Mounting Bracket, Bronze
- NUA-609WH:** Adjustable Mounting Bracket, White

72" Cord and Plug Cable

Convert NUD Series fixtures from hardwire to direct plug-in units.



- NUA-605B:** 72" Cord and Plug, Black
- NUA-605W:** 72" Cord and Plug, White